

RCX-1500



RCX-1500 Play anything. Compromise nothing.



All-in-one performance Music is everywhere. It's in your iPod® and iPhone®, in your CD collection, on terrestrial radio and thousands of other digital radio stations all over the internet. RCX-1500 brings it all together, and delivers it to you with the kind of care and attention to acoustic detail you might only expect from dedicated separates. Pair it with some high-quality speakers, and it could be the only audio equipment you'll ever need.

Your digital gateway The Rotel RCX-1500 opens up a world of digital audio listening. As well as an outstanding CD player, the system has a USB port that makes it easy to hook up your iPhone, iPod, laptop or any other digital music-playing device. Meanwhile, the tuner gives you access to both DAB/FM radio services and internet radio stations from all over the world. To keep your favourite stations handy, there are 30 presets for instant access to FM, DAB and internet broadcasts.



Easy connectivity Plug in the wireless or wired dongle that comes with your RCX-1500, and connecting to the internet couldn't be simpler. Once you're online, you can stream either internet radio or music from any computer connected to your network. What's more, whether you're listening to your iPod or your computer, all of your playlists will be neatly displayed and organised on the RCX-1500's display panel, ready to be accessed and selected by remote control.



Technology and design While RCX-1500 is an all-in-one system, it has been engineered using the kind of high-quality audiophile components you would find in some of our most expensive separates. The CD player uses the same Wolfson DAC as our flagship RCD-1520 player, while the amplifier uses our innovative Class D design that runs cooler while providing enough power to put even the largest floorstanding speakers through their paces.





- 100 Watts x 2 channels
8 ohms
- Wireless or wired connection to access internet radio
- Connect with iPod/MP3/ media music player for home enjoyment
- Access LAN PCs and music with 'Media Player'
- Listen to DAB, FM broadcasts
- Built-in slot loading CD Player
- Available in Black or Silver

RCX-1500		
Amplifier	Continuous Power Output (20-20kHz, <0.3%, 8 ohms)	2 x 100 Watts
	Input Sens/Impedance (AUX2)	200mV/47 Kohms
	Input Overload Level (AUX2)	2.5V
	Frequency Response (AUX2)	10-40kHz (±3dB)
	S/N Ratio (IHF A) (AUX2)	92dB
FM Tuner	Usable Sensitivity	22.2dBf
	Signal to Noise Ratio (at 65dBf)	63dBf (Mono) 60dBf (Stereo)
	Harmonic (at 65dBf)	0.2% (Mono) 0.3% (Stereo)
	Frequency Response	10Hz – 15KHz, ± 3dB
DAB	Sensitivity	-80dBm
	Tuning Range	Band III (174-240MHz)
	Audio Data Rate	224Kbps (Max)
	Frequency Response	20-20KHz, ±1.0dB
	Antenna Input	75 ohms F connector
CD	Total Harmonic Distortion (0dBfs)	0.0045% at 1KHz
	Frequency Response	20-20KHz, ±0.5dB
	Channel Balance	±0.5dB
	Phase Linearity	±0.5 degree
	Channel Separation	90dB at 1KHz
	Signal to Noise Ration (IHF-A)	100dB
	Dynamic Range	96dB
General	Power Consumption	140 Watts
	Power Requirements	120 volts, 60Hz (USA) 230 volts, 50Hz (Europe)
	Dimensions (W x H x D) mm	391 x 143.8 x 343
	Dimensions (W x H x D) in	15 1/3 x 5 3/5 x 13 1/2
	Front Panel Height	3U, 132.6mm, 5 1/4in
	Weight (net)	8.1kg, 17.86lbs

